

# Buy X-Priv Kit

## Smok TFV12 Prince Tank

### Smok X-Priv Replacement Coils

#### Specifications:

**X-Priv Mod**  
 Size: 88x46.5x30.4mm Weight: 172g  
 Power Range: 1W-225W Standby Current: <500uA  
 Output Voltage: 0.5V-9.0V  
 Resistance Range: 0.1Ω-2.5Ω (VW) / 0.05Ω-2Ω (TC)  
 Temperature Range: 200°F --600°F / 100°C --315°C

**TFV12 Prince**  
 Material: Stainless Steel  
 Size: 28x63mm  
 Weight: 60g  
 Capacity: 8ml  
 Thread: 510

#### Verification

- Using your Smartphone or PC visit the SMOK official website: <http://www.smoktech.com/support/>
- Scratch off the coating of the security label on the package to reveal the 16 authentication code. Enter it into the input field on the webpage to verify. The result will be displayed after a few seconds.
- If you have any questions, please contact SMOK via e-mail, phone or our website to get more help.

2

#### Components



4

#### Attach Atomizer

The X-Priv uses a spring loaded 510 connector. Please be certain that there is nothing between the Mod and the attached atomizer.  
 1) Connect the atomizer to the device and tighten it clockwise.  
 2) After the device is powered on, please press the Fire Key to vape.

#### Mod Operations

- Power On:** While the device is off, quickly click Fire Key 5 times in 2s to turn it on. The screen successively displays "SMOK".
- Vaping:**
  - While the device is on, hold Fire Key to vape (it will be forced to stop working when one vaping is longer than 10s, release and press again to vape again);
  - Quickly press the Fire Key 5 times to lock or unlock.
- Screen Unlocked Status:**
  - Press Fire Key and DOWN button simultaneously to choose your desired

6

on the Fire Key to confirm your selected function; UP/DOWN Button can navigate the menu.

#### 1) VW Mode



8

#### 2) TC Mode



- TC Mode is available for X-Priv, only works with a TC type atomizer.
- Enter TC Mode: switch to TC Mode (Ti, Ni, SS), VW Mode and MEMORY Mode by pressing Fire Key + DOWN Button simultaneously while screen is unlocked or by quickly pressing the fire button 3 times and selecting Mode, and then select TEMP.

10

- Enter MEMORY Mode: select from TC Mode, VW Mode and MEMORY Mode by pressing Fire Key + DOWN Button simultaneously while screen is unlocked.
- Wait 5s or press and hold the Fire Key to set M1-M23 settings; increase or decrease the wattage value by UP or DOWN button.

#### 4) Puff Setting



- Puff Setting: Set puff limit number.
- Puff Clear: Puff counter clearing function.
- Puff Already: Puff number taken so far.

12

#### Tank Operation

##### How to fill with e-liquid:

- Hold the tank with one of your hands, and use another one to press button and then move the cap counterclockwise.



- Add e-liquid through the slot, and pay attention to drip it into the central airflow tube.



14

#### Control air input:

Rotate the bottom adjustable airflow system to control air input.



Adjustable Airflow Ring

If you need any additional information or have any questions about the products or its use, please contact your local SMOK agent or to visit our website [www.smoktech.com](http://www.smoktech.com)

16

#### LEGAL DISCLAIMER

Underage sale is prohibited. Depending on your country/region's legal smoking age. 18+ and over 21+ in other countries/regions.

#### WARNING

This product is not intended for use by persons under legal smoking age, nonsmokers, women who are pregnant or breastfeeding, or persons with or at risk of heart disease, high blood pressure, diabetes, or taking medicine for depression or asthma.

#### Appendix 2 Screen Prompts Table

Prompts	Details
"SMOK"	Power on success
"SMOK"	Power off success
BATTERY LOW	Battery voltage is lower than 6.4V
BATTERY HIGH	Input voltage is higher than 9V, you cannot power on
NO ATOMIZER	Atomizer hasn't been detected or the resistance higher than 10Ω
ATOMIZER NEW/OLD	Shows when you change your atomizer
OHM TOO LOW	Low resistance value (≤0.10Ω in VW; ≤0.05Ω in TC) has been detected, replace atomizer

#### Introduction:

X-Priv, a perfect combination of power and beauty. It is covered with glassy material at front, which can offer you a deluxe appearance and a high-definition screen. It employs newly designed UI, more simple and intuitive than other products. And its output power can up to 225W, which can meet different demands of vapor chasers. The fire key of X-Priv is creatively designed on the left side, much easier to operate than before. Moreover, it uses TFV12 Prince tank, with powerful V12 Prince cores you can fully enjoy the massive vapor. Powerful function, fancy appearance, X-Priv is here to conquer you! Innovation keeps changing the vaping experience!

#### The Kit Includes:

- 1 x X-Priv Mod
- 1 x TFV12 Prince Tank
- 1 x V12 Prince-Q4 0.4Ω Quadruple Coils (Pre-installed)
- 1 x V12 Prince-T10 0.12Ω Decuple Coils
- 1 x Replacement Glass Tube
- 1 x User Manual
- 1 x USB Cable
- Spare Parts

1

#### Warranty

Note: Please carefully keep the anti-counterfeiting codes on the package. Only the activated products can get after-sale service.

X-Priv Kit Warranty Period: 6 Months from the Purchase Date.

Within the 6 Months, some items may not be eligible for service due to misuse, damage, or other failures caused by end users. SMOK's warranty only covers manufacturer defects or premature failure. Please contact a SMOK Authorized Vendor for more information and terms of service.

The "X-Priv Kit Customer Card" is an important proof for customers to correctly warranty their kits. Please keep it. Read the card carefully and fill it out properly. Warranty claims must be accompanied with this card. For more warranty policies and processes, please visit our official website: <http://www.smoktech.com/support/>


3

#### Preparation before use:

- Please make sure the battery you're using corresponds with the BATTERY WARNING CARD.
- Before vaping, please make sure the tank is filled with enough e-juice.

#### Battery Installation

- Open the battery cover as the picture shows;
- Place the batteries into the device according to the correct directions;
- Close the battery cover.



5

- mode, TC Mode (Ti, Ni, SS), VW Mode and MEMORY Mode;
- Press Fire Key and UP button to choose your desired ramp up option Norm/Soft/Hard in WATT MODE or 10-225W in TEMP MODE or MEM:1-23 in MEMORY MODE.
- Press UP or DOWN Button to adjust the temperature or wattage settings.

#### 4. Locking your device:

Hold the Fire Key for 5s this will lock your device. No adjustments can be made nor can the device be fired in this state.

**5. Power Off:** While the device is locked, hold Fire Key for 5s, choose POWER OFF, and the screen turns off, which means the device is power off. You may also access the option to turn off your device by entering the menu and selecting the option there.

**6. Settings Saved:** All the settings will be automatically saved when selected. No need to reset your preferences each time the device is turned on.

**7. Menus & Prompts:** After startup, fast press the Fire Key 3 times in 2seconds, then you will go to the operation menu. At the same time long-press

7

- Enter VW Mode: select "WATT" from TC Mode, VW Mode and MEMORY Mode by pressing Fire Key + DOWN Button simultaneously while screen is unlocked. Alternatively you can switch the mode by depressing the fire key three times in quick succession, then press the fire key for a moment while the screen displays "MODE", and then select "WATT" by holding the fire key for a moment.

In the WATT mode, you can use UP / DOWN Button to adjust the wattage settings with an increase/decrease of 0.1W to get the best preferred wattage. ( Note: When the wattage lower than 100 watts the mod will adjust in tenths of a watt initially ; higher than 100 watts the mod will adjust a watt every time).

Use Fire Key to switch to next submenu "Preheat", and use UP or DOWN button to switch your desired ramp up option HARD, NORM, SOFT.

9

- Use Fire Key + UP Button simultaneously to adjust from 10W to 225W.
- In TC Mode, use the UP / DOWN Button to adjust the temperature settings with an increase/decrease of 1 degree Fahrenheit (about 1 Celsius degree) to get the best preferred settings.

#### 3) MEMORY Mode



11

#### 5) Screen Setting



- 6 Colors available for screen display
- Screen Time: 15-240S
- Auto Lock: Lock or Unlock

13

#### 6) Power Off



- Choose "X" means Power On;
- Choose "Y" means Power Off with "SMOK"

13

- Close the cap carefully and firmly. Then let it stand for several minutes to get the organic cotton completely saturated.



#### Replace atomizer core:

First, unscrew the base, then unscrew the coil head from the base, then secure your new coil head onto the base plate (ensure that it is screwed in securely), finally screw the new coil head into the chimney and you're ready to prime your new coil head.



15

#### Attentions

- Before using please read the manual carefully.
- Connect the atomizer to a power source that is suitable for its intended use.
- Please avoid getting the e-liquid into your mouth directly.
- Please do not store liquid inside the tank if it is not going to be used for a long period.
- Please refill the tank when the e-liquid is nearly used to avoid dry-burning of the atomizer.
- Please do not drop, throw or mishandle this product as the outer shell or inner components may be damaged.
- In order to prolong the operation of your product, please keep it away from excessive temperature and humid environment.
- Please keep this product away from children and pregnant women.



17

#### Appendix 1 Key Function Table

Key	Function(Screen Unlock Status)	Function(Screen Locked Status)
Power	Fast click 5 times in 2s – Power On; Fast click 5 times – Screen Locked; Fast click 3 times in 2s – Menu Choose; Hold on – Vape; Release – Standby	Long press 5s – Choose POWER OFF to Power Off; Fast click 5 times – Unlock Screen
UP	Click Down – Increase the temperature (TC Mode) Click Down – Increase the wattage (VW Mode)	
DOWN	Click Down – reduce the temperature (TC Mode) Click Down – reduce the wattage (VW Mode)	
Power + UP	Click Down – Change TC Effect (10-225W) or VW Effect (Hard/Norm/Soft)	
Power + DOWN	Click Down – Change Working Mode (TC / VW / MEMORY)	

OHM TOO HIGH	High resistance value has been detected, replace atomizer
ATOMIZER SHORT	Short circuit has been detected, replace atomizer
TEMPERATURE TOO HIGH	The inner temperature is too high

Welcome to download our APP: Vaping Tour, share your vaping experience and communicate with global vapor fans.

